



marantz



SR5013



7.2 CHANNEL AV RECEIVER WITH HEOS MUSIC STREAMING

The Marantz SR5013 7.2 channel AV receiver offers immersive home theater and high-resolution audio support. Enjoy multi-dimensional surround sound with the latest audio formats in Dolby Atmos, DTS:X and DTS Virtual:X. The SR5013 is fully compatible with the latest HDMI specifications, including 4K video, and lets you stream wireless music from your smart devices via Bluetooth, AirPlay or the HEOS app.

Highlights

- 7.2 channel discrete power amplifier, 100W per channel (8-ohm, 20Hz 20kHz, 0.08% THD)
- 8 HDMI inputs including one HDMI input on the front panel with full HDCP 2.2 support, plus two HDMI outputs
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log-Gamma (HLG)
- Supports object-based audio formats Dolby Atmos, DTS:X and DTS Virtual:X processing
- Ability to decode high-resolution audio ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz plus DSD 2.8MHz and 5.6MHz tracks let you
 enjoy music exactly as the artist intended
- Marantz proprietary HDAM circuit boards for more detailed, dynamic sound
- Built-in HEOS wireless multi-room audio technology
- Amazon Alexa voice control via the HEOS Home Entertainment skill
- Stream the most popular music services like Spotify, Tuneln, Deezer and many others via Bluetooth, AirPlay 2 or the HEOS app
- Integrated Phono input to connect to your turntable
- Optimize your audio experience with Audyssey MultEQ, Dynamic Volume and Dynamic EQ for a seamless setup within your listening environment
- Setup assistant, advanced GUI and Marantz 2016 AVR remote app for an easy out-of-box experience
- Built-in Wi-Fi with 2.4GHz/5GHz dual band support (dual antenna)















































marantz

SR5013

7.2 CHANNEL AV RECEIVER WITH HEOS MUSIC STREAMING





FEATURES	SR5013
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
DTS Virtual:X	•
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auromatic	-/-
Multichannel stereo	•
Max number of processing (Preamp) channels	7.1
Audyssey	MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Compressed audio enhancer: MDAX2	•
NETWORK	
HEOS Multi-room streaming / network audio streaming	• / •
Lossy formats: MP3 / WMA / AAC	• / • / •
Lossless formats: FLAC / ALAC / WAV	• / • / •
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
DSD audio streaming	up to DSD5.6
Gapless playback	 (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	 (AirPlay2 via FW update)
Internet Radio (TuneIn)	• (TuneIn)
Spotify connect / Deezer / TIDAL / Napster / Pandora / SiriusXM	•/•/•/•/•
Compatible with Remote app (iOS/Android)	Marantz 2016 AVR Remote
Ethernet / Wi-Fi	• / • (dual antenna/ dual band)
Bluetooth	•
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	-
Analog to HDMI scaling	480i/576i up to 4K 30/25/24
HDMI to HDMI scaling	up to 4K 30/25/24
GUI overlay on HDMI	•
HDR / HLG / Dolby Vision	• (HDR10) / • / •
3D signal pass-through	•
HDMI pass-through in Standby Mode	•

MULTIROOM / CI HEOS multi-room integrated HEOS Link compatibility: IR/ IP Multi-room zones Zone audio source: HDMI / Opt, Coax / Network, USB / Analog IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI INPUTS/OUTPUTS VIDEO Composite in/out 4+1 / 1 Component in/out Analog In / Out Phono (MM) in Digital in: Optical / Coaxial Multi-room out: Analog / Digital Multichannel pre-out Speaker terminal: gold plated screw / regular screw SPECIFICATIONS Number of speaker terminals Number of speaker terminals 7
HEOS Link compatibility: IR/IP Multi-room zones Zone audio source: HDMI / Opt, Coax / Network, USB / Analog -/-/•/• IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI •/• INPUTS/OUTPUTS VIDEO Composite in/out Component in/out 4+1 /- HDMI in/out Analog In / Out 4+1 /- Phono (MM) in • Digital in: Optical / Coaxial Multi-room out: Analog / Digital 1 /- Multichannel pre-out Subwoofer out 7.1 Multichannel input OTHER Speaker terminal: gold plated screw / regular screw SPECIFICATIONS Number of poweramps 7 Number of speaker terminals
Multi-room zones 2 Zone audio source: HDMI / Opt, Coax / Network, USB / Analog -/-/•/• IP Control / RS232 Control / Web Control / App Control • /• /• /• Domotz Pro / IHIJI • /• INPUTS/OUTPUTS VIDEO Composite in/out 2+1 / 1 Composite in/out 2 / 1 HDMI in/out 7+1 / 2 AUDIO Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI INPUTS/OUTPUTS VIDEO Composite in/out 2+1 / 1 Component in/out 7+1 / 2 AUDIO Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals
P Control / RS232 Control / Web Control / App Control • / • / • / • •
INPUTS/OUTPUTS VIDEO Composite in/out 2+1 / 1 Component in/out 2 / 1 HDMI in/out 7+1 / 2 AUDIO 4+1 / - Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw - / • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
VIDEO Composite in/out 2+1 / 1 Component in/out 2 / 1 HDMI in/out 7+1 / 2 AUDIO 4+1 / - Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw - / • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Composite in/out 2+1 / 1 Component in/out 2 / 1 HDMI in/out 7+1 / 2 AUDIO 4+1 / - Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw - / • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Component in/out 2 / 1 HDMI in/out 7+1 / 2 AUDIO Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
HDMI in/out 7+1 / 2 AUDIO Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
AUDIO Analog In / Out 4+1 /- Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 /- Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Analog In / Out 4+1 / - Phono (MM) in • Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Phono (MM) in Digital in: Optical / Coaxial 2/2 Multi-room out: Analog / Digital 1/- Multichannel pre-out (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/• SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Digital in: Optical / Coaxial 2 / 2 Multi-room out: Analog / Digital 1 / - Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Multi-room out: Analog / Digital 1/- Multichannel pre-out • (7.2) Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Multichannel pre-out Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Subwoofer out 2 7.1 Multichannel input • OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
7.1 Multichannel input OTHER Speaker terminal: gold plated screw / regular screw SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
OTHER Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Speaker terminal: gold plated screw / regular screw -/ • SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
SPECIFICATIONS Number of poweramps 7 Number of speaker terminals 7
Number of poweramps 7 Number of speaker terminals 7
Number of speaker terminals 7
-
Power output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch drive) 100 W
Power output (8 ohm, 20 Hz - 20 kHz, 0.05% 2ch drive) -
Power output (6 ohm, 1 kHz, 10% 1ch drive) 200 W
GENERAL
System remote control RC035SR
Power consumption in W 650
Power consumption no-sound (ECO on / off) in W 45 W / 75 W
Standby consumption in W 0.2 (with CEC 0.5)
Maximum dimensions 17.3 x 13.3 x 6.3 w/o antenna: (W x D x H) in mm
Weight in kg 12.7
Colour Black

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS.X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

^{*} All specs can be subject to change.