

marantz®



## SR8012 11.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY

With unparalleled Marantz performance, the new top-of-the-line SR8012 AV receiver is made for those wanting the ultimate audio and video experience. With a fully symmetrical build, the amplifier features a single board design for its 11 identical amplifier channels, each delivering 205W per channel, for seamless surround sound integration.

### Highlights

11.2 channel AV Receiver with 205W per channel  
 Dolby Atmos and DTS:X (up to 7.1.4 or 9.1.2), Auro-3D  
 Single board per channel power amplifier design; centrally mounted, oversized toroidal transformer; copper-plated chassis  
 High performance 192kHz/32bit D/A converters for all channels  
 Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ  
 Built-in WiFi with 2.4GHz/5GHz dual band support  
 HEOS Music Streaming Technology with HEOS App

---

HEOS HOME ENTERTAINMENT SKILL  
 AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer  
 Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support  
 4K/60 Hz, 4:4:4, HDR and BT.2020, Dolby Vision compatible, HLG  
 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)  
 eARC (Enhanced Audio Return Channel) via future firmware update  
 Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App  
 Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected, IP-control

### Your Benefits

Enough power to fill big rooms with renowned Marantz sound  
 Immersive 3D sound with effects from overhead  
 High-end build-quality for the ultimate in audio performance  
 Highest resolution for music and movie sound  
 Delivering the ultimate equalization for your individual room  
 Improved network stability especially in WiFi-crowded environments  
 Comfortable control options, almost unlimited music sources, and multi-room experience with additional HEOS products

---

Make use of ALEXA VOICE CONTROL  
 Access to almost unlimited online music sources  
 High Resolution audio streaming for HiFi enthusiasts  
 Latest HDMI standard for future-proof compatibility  
 Plenty of inputs for your digital devices; different video in different rooms  
 Allows 3D audio transmission from TV via HDMI audio return channel  
 Hassle-free installation, setup and operation  
 Audio and video in multiple rooms; ready for 3rd Party Home Automation systems



because music matters

## SR8012

### 11.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR8012
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auroomatic	• / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
Audyssey	MultEQ XT32 with LFC/Sub EQ HT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (TuneIn)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	• (via Firmware Update)
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz

\* This feature is not available in all countries.

<b>INPUTS/OUTPUTS</b>	
<b>VIDEO</b>	
Composite In / Out	4+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (2 main + 1 zone)
<b>AUDIO</b>	
Analogue In / Out	6+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (11.2 with 11.2 processing)
Zone audio preout	2
Subwoofer Out	2
7.1 Multichannel input	•
<b>SPECIFICATIONS</b>	
Number of poweramps	11
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	205 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	175 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	140 W
Audio Signal to Noise Ratio	102 dB
<b>GENERAL</b>	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC038SR
Power Consumption in W	780
Power Consumption No-Sound (ECO ...on/off) in W	65 / 110
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 460 x 185
Weight in kg	17.4
<b>EAN</b>	
<b>EU</b>	SR8012/N1B 4951035061008 Black
	SR8012/N1SG 4951035061015 Silvergold
<b>UK</b>	SR8012/T1B 4951035061022 Black
	SR8012/T1SG 4951035061039 Silvergold

Sound United Europe  
A Division of D&M Europe B.V.  
Beemdstraat 11  
5653 MA Eindhoven  
The Netherlands

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.