

**AVAILABLE AT DIGITAL CINEMA** 



### NA6006

# NETWORK AUDIO PLAYER / STREAMER






Born from the success of the award-winning ND8006, the Marantz NA6006 Streamer is the perfect choice for demanding yet price-conscious digital music lovers. Stream music from Spotify, Deezer, TIDAL and more, and enjoy playback of DSD (2.8/5.6 Mhz), WAV, MP3, AAC, WMA, FLAC and ALAC files. Seamlessly control the NA6006 with your voice and Amazon Alexa (Echo device required) when you download the HEOS Home Entertainment Skill.

Highlights	<b>Your Benefits</b>
------------	----------------------

High quality digital music streamer	Perfect addition to complement any existing amplifier
AirPlay 2, Bluetooth, Internet Radio, Spotify Connect, Amazon Music, TIDAL, Deezer and more	Access to almost unlimited online music sources (where available)
Audiophile 192kHz/32bit D/A conversion (ESS9016) and dual crystal clock	Most accurate conversion and sound quality from all sources
Marantz proprietary HDAM circuits	Wider dynamic range with lower distortion for the analogue output stage
Full discrete headphone amplifier with gain control	High-quality sound even from demanding headphones
Built-in Wi-Fi with 2.4GHz/5GHz dual band support	Improved network stability especially in Wi-Fi-crowded homes
Built-in HEOS Wireless Multi-Room Audio Technology	Comfortable multiroom audio with other HEOS products, controlled by app
HEOS HOME ENTERTAINMENT SKILL	Make use of ALEXA VOICE CONTROL
Support of WAV, MP3, AAC, WMA, FLAC, ALAC file playback via USB devices	Plays most popular digital media files, including high resolution
Optical input/output; variable and fixed analogue outputs	Multiple connections and custom installation options
Available in black or silver-gold	Perfectly matching to Marantz Amplifiers



























# marantz<sup>®</sup>

# NA6006

# NETWORK AUDIO PLAYER / STREAMER



CD Compatibility: CD / CD-R/RW / WMA / MP3 / AAC  CD-Text / ID3 Tag / WMA Meta Tag / AAC Meta data  -/ • / • / • / •  WiFi / Bluetooth / Spotify Connect / AirPlay 2  Network & Online Music Streaming  HEOS Multiroom integrated  Front USB  Digital Optical in / out  Analogue out  Fixed & Variable  HDAM version  HDAM & HDAM SA2  Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossys formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  • (2.8 MHz / 5.6 MHz)  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Fixed & Variable	FEATURES	NA6006
CD-Text / ID3 Tag / WMA Meta Tag / AAC Meta data  WiFi / Bluetooth / Spotify Connect / AirPlay 2  Network & Online Music Streaming  HEOS Multiroom integrated  Front USB  Digital Optical in / out  Analogue out  Fixed & Variable  HDAM version  HDAM & HDAM SA2  Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats FLAC / ALAC / WAV  DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Sample Rate digital In  Marantz remote bus  RS232  -    -    O -   O	CD Compatibility: CD / CD-R/RW / WMA / MP3 / AAC	• / • / • / • / •
WiFi / Bluetooth / Spotify Connect / AirPlay 2  Network & Online Music Streaming  HEOS Multiroom integrated  Front USB  Digital Optical in / out  Analogue out  HDAM version  HDAM & HDAM & HDAM SA2  Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  Barber Rade (Audroid/iOS)  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Marantz remote bus  RS232  - ' • / • / • / • / • / • / • / • / • / •	CD-Text / ID3 Tag / WMA Meta Tag / AAC Meta data	-/•/-
HEOS Multiroom integrated Front USB  Digital Optical in / out  Analogue out  HDAM version  HDAM version  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Marantz remote bus  RS232  -  IPAM SA Variable  Fixed & Variable  •  Fixed & Variable  Fixed & Variable  •  Fixed & Variable  Fixed &		• / • / • / •
Front USB  Digital Optical in / out  Analogue out  Fixed & Variable  HDAM version  HDAM & HDAM SA2  Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Marantz remote bus  RS232  -   -  -  -  -  -  -  -  -  -  -  -	Network & Online Music Streaming	•
Digital Optical in / out  Analogue out  HDAM version  HDAM & HDAM & HDAM SA2  Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Anantz remote bus  RS232  -   FIXAM & Variable  Fixed & Variable  •  Fixed & Variable	HEOS Multiroom integrated	•
Analogue out  HDAM version  Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Marantz remote bus  RS232  -   Fixed & Variable  HDAM & HDAM & HDAM SA2  HDAM & HDAM SA2  HDAM & HDAM SA2  + (dual antenna / dual band)  - (**) (** (dual antenna / dual band)  - (**) (**) (**) (**) (**) (**) (**) (**	Front USB	•
HDAM version Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi AirPlay 2 Internet Radio (Tuneln)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud* Lossy formats MP3 / WMA / AAC Lossless formats FLAC / ALAC / WAV  DSD Streaming FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In Analogue out Ethernet port Digital Inputs: Coaxial / Optical Digital Outputs: Coaxial / Optical Marantz remote bus  RS232  -   HDAM & HDAM & HDAM SA2  •  (HUAC)  (HUAC)  (HUAC)  (HUAC) (	Digital Optical in / out	• / •
Headphone Output  High Grade Audio Components  Marantz Musical Digital Filtering  •	Analogue out	Fixed & Variable
High Grade Audio Components  Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi	HDAM version	HDAM & HDAM SA2
Marantz Musical Digital Filtering  NETWORK MUSIC STREAMING  Ethernet / Wi-Fi  AirPlay 2  Internet Radio (TuneIn)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*  Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  DSD Streaming  (2.8 MHz / 5.6 MHz)  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Marantz remote bus  RS232  - (dual antenna / dual band)  - (e)	Headphone Output	•
NETWORK MUSIC STREAMING         Ethernet / Wi-Fi       ● / ● (dual antenna / dual band)         AirPlay 2       ●         Internet Radio (TuneIn)       ●         Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*       ● / ● / ● / ●         Lossy formats MP3 / WMA / AAC       ● / ● / ●         Lossless formats FLAC / ALAC / WAV       ● / ● / ●         DSD Streaming       ● (2.8 MHz / 5.6 MHz)         FLAC HD 192/24 / WAV 192/24 / ALAC 192/24       ● / ● / ●         Gapless playback       ● (FLAC, WAV, ALAC, DSD)         Compatible with Remote App for Smart Phones       ● (Android/iOS)         INPUTS / OUTPUTS         Sample Rate Front USB In       192 kHz / 24-bit & DSD2.8 / DSD5.6         Analogue out       Fixed & Variable         Ethernet port       ●         Digital Inputs: Coaxial / Optical       - / ●         Digital Outputs: Coaxial / Optical       - / ●         Sample Rate digital In       192 kHz / 24-bit         Marantz remote bus       ●         RS232       -	High Grade Audio Components	•
Ethernet / Wi-Fi	Marantz Musical Digital Filtering	•
AirPlay 2 Internet Radio (TuneIn)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*	NETWORK MUSIC STREAMING	
Internet Radio (TuneIn)  Spotify Connect, Deezer, TIDAL, Napster, Soundcloud*	Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud * • / • / • / • / • .  Lossy formats MP3 / WMA / AAC • / • / • .  Lossless formats FLAC / ALAC / WAV • / • / • .  DSD Streaming • (2.8 MHz / 5.6 MHz)  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24 • / • / • .  Gapless playback • (FLAC, WAV, ALAC, DSD)  Compatible with Remote App for Smart Phones • (Android/iOS)  INPUTS / OUTPUTS  Sample Rate Front USB In 192 kHz / 24-bit & DSD2.8 / DSD5.6  Analogue out Fixed & Variable  Ethernet port • .  Digital Inputs: Coaxial / Optical -/ • .  Digital Outputs: Coaxial / Optical -/ • .  Sample Rate digital In 192 kHz / 24-bit  Marantz remote bus • .  RS232	AirPlay 2	•
Lossy formats MP3 / WMA / AAC  Lossless formats FLAC / ALAC / WAV  P - ( • ( • ) • ( •	Internet Radio (TuneIn)	•
Lossless formats FLAC / ALAC / WAV  DSD Streaming FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  of paless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out Fixed & Variable  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Sample Rate digital In  Marantz remote bus  P (2.8 MHz / 5.6 MHz)  (FLAC, WAV, ALAC, DSD)  (Android/iOS)  Fixed & Variable  Fixed & Variable  - / •  192 kHz / 24-bit & DSD2.8 / DSD5.6  - / •  192 kHz / 24-bit	Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	•/•/•/•
DSD Streaming  FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Sample Rate digital In  Marantz remote bus  (2.8 MHz / 5.6 MHz)  (AHZ / 4-  (FLAC, WAV, ALAC, DSD)  (Android/ioS)  INPUTS / OUTPUTS  192 kHz / 24-bit & DSD2.8 / DSD5.6  Fixed & Variable  - / •  192 kHz / 24-bit & DSD2.8 / DSD5.6  192 kHz / 24-bit & DSD2.8 / DSD5.6  192 kHz / 24-bit	Lossy formats MP3 / WMA / AAC	• / • / •
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24  Gapless playback  • (FLAC, WAV, ALAC, DSD)  Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Sample Rate digital In  Marantz remote bus  RS232  • (FLAC, WAV, ALAC, DSD)  • (Android/ioS)  INPUTS / OUTPUTS  • (Android/ioS)  Fixed & Variable  • (FLAC, WAV, ALAC, DSD)  • (Android/ioS)  INPUTS / OUTPUTS  • (Android/ioS)  INPUTS / OUTPUTS   • (Android/ioS)  INPUTS / OUTPUTS  • (Android/ioS)  • (Android/ioS)  INPUTS / OUTPUTS  • (	Lossless formats FLAC / ALAC / WAV	• / • / •
Gapless playback  Compatible with Remote App for Smart Phones  (Android/iOS)  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Sample Rate digital In  Marantz remote bus  (FLAC, WAV, ALAC, DSD)  (Android/iOS)  192 kHz / 24-bit & DSD2.8 / DSD5.6  Fixed & Variable  - / •  192 kHz / 24-bit  192 kHz / 24-bit	DSD Streaming	• (2.8 MHz / 5.6 MHz)
Compatible with Remote App for Smart Phones  INPUTS / OUTPUTS  Sample Rate Front USB In  Analogue out  Ethernet port  Digital Inputs: Coaxial / Optical  Digital Outputs: Coaxial / Optical  Sample Rate digital In  Marantz remote bus  (Android/iOS)  192 kHz / 24-bit & DSD2.8 / DSD5.6  Fixed & Variable  Fixed & Variable	FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
INPUTS / OUTPUTS           Sample Rate Front USB In         192 kHz / 24-bit & DSD2.8 / DSD5.6           Analogue out         Fixed & Variable           Ethernet port         •           Digital Inputs: Coaxial / Optical         - / ●           Digital Outputs: Coaxial / Optical         - / ●           Sample Rate digital In         192 kHz / 24-bit           Marantz remote bus         •           RS232         -	Gapless playback	• (FLAC, WAV, ALAC, DSD)
Sample Rate Front USB In       192 kHz / 24-bit & DSD2.8 / DSD5.6         Analogue out       Fixed & Variable         Ethernet port       •         Digital Inputs: Coaxial / Optical       - / •         Digital Outputs: Coaxial / Optical       - / •         Sample Rate digital In       192 kHz / 24-bit         Marantz remote bus       •         RS232       -	Compatible with Remote App for Smart Phones	• (Android/iOS)
Analogue out Fixed & Variable  Ethernet port  Digital Inputs: Coaxial / Optical -/ •  Digital Outputs: Coaxial / Optical -/ •  Sample Rate digital In 192 kHz / 24-bit  Marantz remote bus  RS232 -	INPUTS / OUTPUTS	
Ethernet port         ●           Digital Inputs: Coaxial / Optical         - / ●           Digital Outputs: Coaxial / Optical         - / ●           Sample Rate digital In         192 kHz / 24-bit           Marantz remote bus         ●           RS232         -	Sample Rate Front USB In	192 kHz / 24-bit & DSD2.8 / DSD5.6
Digital Inputs: Coaxial / Optical         - / ●           Digital Outputs: Coaxial / Optical         - / ●           Sample Rate digital In         192 kHz / 24-bit           Marantz remote bus         ●           RS232         -	Analogue out	Fixed & Variable
Digital Outputs: Coaxial / Optical - / •  Sample Rate digital In 192 kHz / 24-bit  Marantz remote bus •  RS232 -	Ethernet port	•
Sample Rate digital In         192 kHz / 24-bit           Marantz remote bus         ●           RS232         -	Digital Inputs: Coaxial / Optical	- / •
Marantz remote bus • RS232 -	Digital Outputs: Coaxial / Optical	- / •
RS232 -	Sample Rate digital In	192 kHz / 24-bit
	Marantz remote bus	•
Headphone Out •	RS232	-
	Headphone Out	•

SPEC	IFICATIONS		
D/A Conversion			ESS Hyper Stream
DAC IC			ES9016
Low Pass Filter stage			HDAM
Output Buffer			HDAM SA2
Head	ohone amp		HDAM SA2
GENI	RAL		
Available colors			Black / Silver-Gold
Metal Front Panel			•
Power Consumption			35 W
Standby Consumption			0.2 W
Auto Power off			•
Detachable Power Cable			•
Remote Control			RC005NA
System Remote Function			•
Maximum Dimensions (W x D x H)		440 x 329 x 106 mm	
Weight			6.6 kg
EAN			
EU	NA6006/N1B	4951035065730	Black
	NA6006/N1SG	4951035065747	Silver-Gold
UK	NA6006/T1B	4951035066768	Black
	NA6006/T1SG	4951035066775	Silver-Gold

Sound United Europe A Division of D&M Europe B.V. Beemdstraat 11 5653 MA Eindhoven The Netherlands The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

IV01I

<sup>\*</sup> All specs can be subject to change.