



# TX-RZ3100 11.2-Channel Network A/V Receiver























































## For Multidimensional Sound Without Compromise

Our flagship A/V receiver's fathomless high-current power and lightning dynamic performance make it the ultimate in 7.2.4-channel home cinema. Match with floorstanding speakers and in-ceiling height speakers for accurate, lush, and exuberant sound that transports your audience into the film director's world. As well as transcendent cinema and stereo music, the TX-RZ3100 serves entertainment around your home with wired or wireless multi-zone audio, Zone 2 HDMI®, and network audio platforms including Chromecast built-in\*, FlareConnect\*\*, and DTS Play-Fi®\* that stream music from apps to the home cinema and beyond. Select HDMI terminals enable 4K/60p video with BT.2020, 4:4:4 color space, and HDR (HDR10/Dolby Vision™) pass-through for spectacular images on the latest TVs and projectors. Ready for custom home integration, the TX-RZ3100 is crafted with passion for the passionate listener. \* Enabled with a firmware update

#### **HIGHLIGHTS**

- · 200 W per Channel
- THX® Select2™ Plus Certification
- DTS:X® and Dolby Atmos® to 7.2.4 Channels
- DTS Neural:X™ Upmixing for Legacy Multichannel Formats
- Chromecast built-in\*1, AirPlay, DTS Play-Fi®\*1, Wi-Fi®, and Bluetooth® Audio Streaming
- AccuEQ Room Calibration with AccuReflex Technology
- FlareConnect<sup>™\*|</sup> Multi-Room Wireless Technology
- HDMI® 8 In (1 Front), Main Out, Zone 2 Out (HDCP 2.2/HDR Pass-through\*2)

#### ADVANCED FEATURES

- THX® Select2™ Plus Cinema-Reference Audio Performance
- 7.2.4-channel DTS:X and Dolby Atmos Object-based Audio Decoding • DTS Neural:X Upmixes Standard 5.1 and 7.1 formats to 3D Sound
- HDMI Supports 4K/60 Hz, BT.2020, HDR (HDR I 0/Dolby Vision \*\*\*!) Pass-through, 4:4:4 Color Space, and HDCP 2.2-protected Video\*\*2
- Chromecast built-in, DTS Play-Fi, AirPlay, Wi-Fi, Bluetooth, TuneIn, Spotify®, TIDAL\*1, and Deezer\*1 Audio Streaming\*3
- MP3, WMA, WMA Lossless, FLAC, WAV, AAC, and Apple Lossless Playback Over Network and USB
  Network Hi-Res Audio (DSD 11.2 MHz, 192/24 PCM, Dolby® TrueHD)
- Powered Zone 2 and Powered Zone 3 Outputs for Multi-room Analog and Digital (HDMI/Network/OPT/COAX) Audio with Independent Volume/Tone Controls
- Whole House Mode
- AccuEQ Calibration with AccuReflex for Seamless Object-based, Multichannel, and Stereo Sound (Setup Mic Included)

- FlareConnect Multi-room Audio Distribution to Compatible
- Components and Speakers

   11.2 Multichannel Pre-Outs for User Setup Customization
- Quality Banana-plug Speaker Posts with Transparent Knobs Onkyo Controller<sup>\*4</sup> App for iOS and Android<sup>™</sup> Devices

#### **AMPLIFIER FEATURES**

- 200 W/Ch (6  $\Omega$ , 1 kHz, 1% THD, 1 Channel Driven, IEC) 340 W/Ch (6  $\Omega$ , 1 kHz, 10% THD, 1 Channel Driven, [EITA)
- Onkyo High-Current Digital Amplification for Smooth Low-Distortion Power
- Customized High-Output Transformer, Custom Audio-Grade Capacitors, Separate Transformer for Standby
   Separated Digital and Analog Circuitry to Reduce Interference
- Extruded Metal Heat Sink with Polycarbonate Cooling Fan
- Optimum Gain Volume Circuitry
- VLSC™ (Vector Linear Shaping Circuitry) Noise-free Signal Processing for All Channels
- PLL (Phase Locked Loop) Jitter-Cleaning Circuitry for S/PDIF Audio

#### PROCESSING FEATURES

- \*\*HDMI Support for 4K/60 Hz, 3D, Audio Return Channel, DeepColor\*\*, x.v.Color\*\*, LipSync, Dolby Atmos, Dolby TrueHD, Dolby\* Digital Plus, Dolby\* Surround, DTS:X, DTS-HD Master Audio\*\*, DTS 96/24, DTS-ES, DTS Express, DTS Neural:X, THX\*\* © Cimeni/Music/Game, DVD-Audio, Super Audio CD, Multichannel PCM, and CEC
- Dolby Atmos, DTS:X, Dolby TrueHD, and DTS-HD Mas
- Separate 384 kHz/32-bit AK4490 Stereo DAC (Front L/R), 2 x 768 kHz/32-bit AK4458 Multichannel DACs (Surround Channels)
- Discrete 192 kHz/24-bit AK4388 Stereo DACs (x2) for Zone 2 and Zone 3
- Multiple 32-bit Digital Signal Processing Engines
- 4 DSP Modes for Gaming: Rock, Sports, Action, and RPG Theater-Dimensional Virtual Surround Function
- Direct Mode and Pure Audio Mode

#### **CONNECTION FEATURES**

- 8 HDMI Inputs (I Front/7 Rear), Main, and Zone 2 Outputs
- Component Video Switching (2 Inputs and 1 Output) and 2 Composite Video Inputs
- 5 Digital Audio Inputs (3 Optical and 2 Coaxial) and 7 Analog Audio Inputs
- Phono Input (MM) for Turntable Connection
- Mass Storage Class USB Memory Playback Capability (Rear Input)
- Zone 2 and Zone 3 Powered Speaker Outputs
- 11.2 Multichannel Pre-Outs and Zone 2/3 Pre-/Line Outs
- · Dual Subwoofer Pre-Outs
- 12 V Trigger Out (Assignable) with IR Input; Supports IP and RS232
- 6.3 mm Headphone Input

#### OTHER FEATURES • Tone Controls (Bass/Treble) ±10 dB for All Channels

- Independent Crossover Adjustment for Each Channel (40/50/60/70/80/90/100/120/150/180/200 Hz)
- $\bullet$  A/V Sync Control (Up to 500 ms in 5 ms Steps at 48 kHz)
- New Graphical Overlaid On-Screen Display (OSD) via HDMI with
- Ouick Setup Function
- Hybrid Standby Function with HDMI Passthrough
- 40 FM/AM and 40 Internet Radio Station Presets
- RIHD (Remote Interactive Over HDMI) for System Control
- Aluminum Front Panel and Volume Control Knob
- Simple Remote Control
- \*I Enabled with a firmware update. \*2 6G Videal/HDR/HDCP 2.2 supported on HDMI inputs 1–5, Main Out, and Zone 2 Out \*\*3 Availability of services depends on region Some services m require a paid subscription and firmware update Availability of third-party services advertised he is accurate at the time of publication, but may be subject to change without notice. \*4 For iOS and Andraid\* devices. Please check App Store or Coogle Ploy for device and OS requirements.

## TX-RZ 3100 11.2-Channel Network A/V Receiver

#### Ultimate DTS:X® and Dolby Atmos® Home Cinema

With 11.2 channels of instantaneous power from an uncommonly small body, the TX-RZ3100 enables the current

maximum Dolby Atmos and DTS:X home-cinema layout of 7.2.4 channels in a self-contained component for the ultimate in multidimensional objectbased surround-sound.



#### **Upmixes Standard Surround Formats**

DTS Neural: $X^{\mathsf{m}}$  retrieves spacial cues from standard multichannel formats and upmixes for 3D playback that's virtually identical to a native DTS:X source, giving your existing Blu-ray library a new lease on life.

#### THX®-Certified for Cinema Reference Sound

THX® Select2™ Plus guarantees distortion-free Cinema Reference Volume in your home. Certified products are subjected to the industry's toughest bench-tests to satisfy THX® requirements for audio performance

#### Onkyo High-Current Digital Amplification

The TX-RZ3100 combines high-current driving architecture with sophisticated digital amplification and filtering technology. Noise-reduction hardware including a new custom low-hum

transformer delivers fast dynamics, thrilling power, and stunningly precise detail resolution. Painstakingly tuned for velvet-smooth and emotionally evocative audio reproduction, Onkyo High-Current Digital is where power meets control.



#### Cohesive Multidimensional Sound

AccuReflex—part of the AccuEO room calibration suite phase-matches Dolby Atmos-enabled and floor-standing speakers for seamless reproduction of object-based sound. AccuEQ optimizes the entire system to suit your space without affecting front-speaker characteristics for pure stereo





#### Chromecast built-in\*, DTS Play-Fi®\*, AirPlay, Wi-Fi®, and Bluetooth®

Popular smartphone and PC music apps let you mirror what's playing to your TX-RZ3100 with ease using Chromecast built-in and DTS Play-Fi. The receiver also features AirPlay, Bluetooth, and Wi-Fi for universal wireless audio support, including DSD up to 11.2 MHz. \* Enabled with a firmware update

#### Spotify®, Deezer, TIDAL, and TuneIn

Enjoy the music you want any time on your home cinema via these popular smartphone and PC applications or via Onkyo Controller.

#### FlareConnect<sup>™</sup> Wireless Multi-room Audio

FlareConnect\* shares audio from network and external audio input sources between compatible components. Enjoy effortless multi-room playback of LP records, CDs, network music services, and more with supported components and speaker systems. Music selection, speaker grouping, and playback management across the home are built into the Onkyo Controller\*\* app.



Sharing audio from external inputs is enabled with a future firmware update. External audio inputs supporting FlareConnect may differ depending on model. Hease consult individual product specification for more information. free from the App Store or Google Play

#### Housewide Playback of Any Source

Put extra speakers you have to good use—connect them to the receiver's Powered Zone 2 and Powered Zone 3 outputs. Dedicated DACs and smartphone control options let you manage content in any zone, making housewide sound a practical proposition.

#### Latest Dual-Zone HDMI®

Select HDMI terminals support HDR (HDR10/Dolby Vision™\*) pass-through, 4:4:4 color-space, BT.2020, and HDCP 2.2 for next-generation Ultra HD Blu-ray, streaming 4K video, and 4K/60 Hz PC-based gaming. Zone 2 output transmits 4K home cinema sources to a second TV.

#### **SPECIFICATIONS**

Amplifier Section Power Output	
All Channels	200 W/Ch (6 Ω, I kHz, I%THD, I Channel Driven, IEC) 340 W/Ch (6 Ω, I kHz, I0%THD, I Channel Driven, IEITA)
Dynamic Power	320 W (3 Ω, Front) 270 W (4 Ω, Front) 160 W (8 Ω, Front)
THD+N (Total Harm	onic Distortion + Noise)
	0.04% (1 kHz, 100 W)
Input Sensitivity and I	
	200 mV/82 k $\Omega$ (Line) 3.5 mV/47 k $\Omega$ (Phono MM)
Rated RCA Output L	
reaced record Output D	I.0V/330 Ω (Pre Out)
	I.0 V/330 Ω (Subwoofer Pre Out)
	200 mV/1.2 kΩ (Zone Out)
	2.0 V/1.2 kΩ (Zone Pre Out)
Phono Overload	70 mV (MM, 1 kHz, 0.5%)
Tone Control	±10 dB, 100 Hz (Bass) ±10 dB, 10 kHz (Treble)
Signal-to-Noise Ratio	

#### Speaker Impedance **Video Section**

put Sensitivity/Output Level and Impedance		
Video	$1.0 \text{ Vp-p/75 } \Omega \text{ (Component Y)}$	
	0.7 Vp−p/75 Ω (Component PB/CB, PR/CR)	
	I.0 Vp-p/75 Ω (Composite)	

4 Ω – 16 Ω

90 dB (Phono MM, IHF-A)

#### Component Video Frequency Response

	5 Hz-100 MHz/+0 dB, -3 dB	
Tuner Section		
Tuning Frequency Range		
FM	87.5 MHz-108 MHz	
	87.5 MHz-107.9 MHz (Taiwan Model)	
AM	530 kHz-1,710 kHz	
	522 kHz-1,611 kHz	
	522 kHz-1,611 kHz (Taiwan Model)	
FM/AM Preset Memory	40 Stations	
General		
Power Supply	AC 220-230 V~, 50/60 Hz	
	AC 120 V~, 60 Hz (Taiwan Model)	
Power Consumption	340 W	
Standby Power Consumption		

### Weight

CARTON	
Dimensions (W x H x D)	565 x 325 x 547 mm
Weight	22.5 kg

19.7 kg

#### **Supplied Accessories**

Dimensions (W  $\times$  H  $\times$  D) 435  $\times$  201

- Indoor FM antenna AM loop antenna Speaker setup microph Instruction manual Remote controller AA (R6) batteries × 2<sup>st</sup>

<sup>\*</sup> Batteries not included with Chinese model variants



Text on receiver may

Due to a policy of continuous product improvement, Onlyo reserves the right to change specifications and appearance without notice. THX the THX logo, and Select2 are trademarks of THX Ltd.THX and the THX logo are registered in the US. and other jurisdictions. All rights reserved Manufactured under license from Dolby, Laboratories. Dolby, Dolby, Atmos, Dolby, Surround, Dolby, Vision, and the double-D symbol are trademarks of DTS patents, see http://patents.dts.com. Manufactured under license from DTS, Inc. DTS, the Symbol, DTS and the Symbol together, DTSX, the DTSX logo, Play-Fi, and the Play-Fi logo are registered trademarks or Trademarks of DTS, Inc. and Fights Reserved. HDPMI, the HDPMI logo, and High-Definition Multimedia Interface are trademarks or ThY and the United States and/or other countries. BD DTS, Inc. All Rights Reserved. HDPMI, the HDPMI logo, and High-Definition Multimedia Interface are trademarks or ThY and the United States and or the United States are trademarks or Play-Fight Play-Definition Multimedia Interface are trademarks or Play-Definition Play-Def



<sup>\*</sup> Enabled with a firmware update