



FM/DAB+TUNER

T11







RDS (Radio Data System) capability for FM broadcasts



Includes remote control

Rotel has been producing quality tuners since the 1960s. One of the latest additions to this long-established line-up is the T11 FM/DAB+ tuner. It provides a wealth of listening options with easy access to classic analogue FM stations as well as newer DAB+ (Digital Audio Broadcasting) services. Like the

T14, T11 features the ability to easily store and recall up to 30 presets each for FM or DAB+ stations. A further useful feature common to all 14 Series products is the ability to dim the display panel and power LED to provide a comfortable visual reference in all lighting environments.

Rotel tuners provide a wealth of high quality listening choices. See more at

rotel.com





## FM/DAB+TUNER

## T11



## **SPECIFICATIONS**

**FM Tuner** 

**Usable Sensitivity** 22.2 dBf

**50dB Quieting Sensitivity** 27.2 dBf (mono)

Signal to Noise Ratio

Mono 63 dBf (at 65 dBf) Stereo 60 dBf (at 65 dBf)

**Harmonic Distortion** 

 Mono
 0.2% (at 65 dBf)

 Stereo
 0.3% (at 65 dBf)

 Frequency Response
 10Hz - 15kHz, ± 3dB

 Stereo Separation
 40 dB / 37 dB

(100Hz/1kHz)

Analog Output 1.0 V

**Antenna Input** 75 Ohms F connector

DAB Tuner

Sensitivity -80 dBm

**Tuning Range** Band III (174 - 240MHz)

Audio Data Rate224kbps (Max)Frequency Response20 - 20kHz, +/- 1.0 dBAnalog Output2.1V at 0 dBFSAntenna Input75 Ohms F connector

Genera

Power Requirements (AC)

Europe 230V, 50Hz
USA 120V, 60Hz

Power Consumption 10 watts

Standby Power Consumption < 0.5 watts

Finishes Silver and Black

Dimensions (W x H x D) 430 x 73 x 331mm

 $17" \times 27/8" \times 13"$  Front Panel Height 60mm, 2 3/8" Weight (net) 4.3 kg, 9.5 lb

Rotel tuners provide a wealth of high quality listening choices. See more at

